

4/PR TS

WO 00/45183

1

09/890126  
JO Rec'd PCT/PTO 27 JUL 2001  
PCT/IE00/00012

ELECTRICAL ENERGY METER

This invention relates to electrical energy meters and to a current probe for use in such meters.

5

Standard electro-mechanical electrical energy meters have some or all of the following disadvantages.

They all consume a significant amount of power to  
10 operate. The IEC standard for class II meters is <2 watts. This power consumption amounts to between .25% to .5% of all power consumed. Losses due to metering are therefore substantial.

15 They have inertia problems when starting; therefore they must have a certain amount of power being drawn before they start to register.

They can only be installed by skilled personnel, and  
20 their installation is time-consuming. Electro-mechanical meters need to be fixed firmly to a flat surface in an upright position. In territories such as the former Soviet Union when metering is being installed in volume for the first time, the cost of  
25 installation of the electro-mechanical meters is high.

In conventional one wire current probes (see Fig. 1), a loop 1 of magnetic material surrounds a current carrying conductor 2 and a coil 3 comprising a large  
30 number of turns of wire is wound on the magnetic material 1. This type of probe relies on Ampere's Law which states that the integral of the magnetic field

around a closed loop surrounding a current source is equal to the current enclosed.

In a well designed probe of this kind the voltage or  
5 current induced in the coil 3 is not dependent on the position of the source current (conductor 2) within the cross section surrounded by the closed magnetic core 1. Furthermore, the ratio of pickup voltage or current from the current source 2 within the closed magnetic  
10 ring core 1, compared to the pickup from the same source when it is located outside the closed magnetic ring core is very large, e.g. >1000:1.

This ensures that stray pickup from interfering current  
15 sources which may be located close to the probe but outside the magnetic ring core do not affect the measurements obtained from the required source which is located inside.

20 One of the disadvantages of this type of probe however is its cost. The magnetic core must be manufactured in two or more sections to allow the core to be opened and closed so that the conductor can be inserted. In order to make an accurate measurement the alignment of the  
25 two sections on closing is critical, as is the requirement that even a small air gap between sections on meeting is not allowed.

US Patent No. 5,057,769 discloses a probe having a gap  
30 4 (see Fig. 2) in a continuously wound non-magnetic core coil 5 to allow the insertion of the current source. In order to maintain the desirable features of the continuous winding closed non-magnetic core 5, an

effort is made to add back in the voltage component that would have been picked up by the coil turns which were removed to provide the air gap 4, by adding two individual multi-turn coils 6 at either side of the gap

5 4.

Even with the correct number of turns in these coils this is only partly successful. The voltage pickup of the probe is dependent on the location of the source

10 conductor within the internal cross section of the coil. The closer the source current carrying conductor is to the gap or the windings, and the larger the gap, the greater the variation in pickup.

15 Furthermore, with this design, the pickup from sources in area 7 outside the core gap cross-section is no longer negligible and the pickup from an external current source increases as the gap increases, or as the external sources approach the gap. This can pose a

20 serious limitation especially when measurements are being performed in a distribution box for example, where there may be a large number of conductors carrying various currents in a confined space.

25 It is an object of the invention to provide a low cost, low power meter which is quick and easy to install and which may, if desired, be retro-fitted to existing mains installations. In particular, it is an object to provide a meter which may be fitted easily to domestic

30 power supplies.

It is a further object to provide an improved probe exhibiting less interference from external sources than

in the prior art, without resorting to expensive designs.

According to the present invention there is provided an  
5 electrical energy meter comprising an electrically  
insulating housing for securing relative to least two  
mains cables each having a conductive core surrounded  
by a sheath of insulating material, the housing  
including respective electrical contact means for  
10 piercing the insulating sheath of each cable to make  
contact with the core, sensing means for providing an  
output corresponding to the current flowing in at least  
one of the cables, and circuit means for calculating  
and displaying electrical energy as a function of the  
15 voltage across the contact means and the output of the  
sensing means.

In a further aspect, the invention provides a current  
probe for measuring current in a conductor, comprising  
20 a plurality of coils connected together in series in an  
arrangement which substantially surrounds the cable in  
which current is to be measured.

Preferably, said coils are substantially equidistantly  
25 spaced in the form of an open loop, with a gap being  
provided between two of the coils in the loop, said gap  
enabling introduction of the conductor into the  
interior of the loop.

30 In a particularly preferred current probe, the coils  
are arranged in two concentric loops of coils, each  
loop being connected in series, and each loop having a  
gap between two of the coils in the loop, said gaps

enabling introduction of the conductor into the interior of the concentric loops.

Preferably, in such an embodiment, there is also provided an electronic circuit for comparing the pickup from external sources experienced by each of the two loops and providing an output which compensates for such pickup, based on the respective dimensions of the loops.

10

An embodiment of the invention will now be described, by way of example, with reference to the accompanying drawings, in which:

15 Fig. 1 is an illustration of a first known current probe arrangement;

Fig. 2 is an illustration of a second known current probe arrangement;

20

Fig. 3 is a perspective view of a meter according to the invention with the front plate removed;

Fig. 4 is a top plan view of the front plate of the meter of Fig. 5;

25

Fig. 5 is a horizontal cross-section through the meter;

Fig. 6 illustrates a security device for the meter;

30

Fig. 7 is a diagram of a current probe according to the invention schematically illustrating the arrangement of coils in the meter of Figs. 3-6;

Fig. 8 is a sectional plan view of a detail of the meter of Figs. 3-6 showing the arrangement of coils therein; and

5.

Fig. 9 is a diagram of an alternative current probe according to the invention which can be incorporated in the meters of the invention.

- 10 In the following description, expressions of orientation are used for convenience only and are not intended to limit the orientation of the meter in use.

Referring to Figs. 3-5, an electrical energy meter is shown for measuring and displaying the amount of energy supplied by a pair of mains live and neutral cables 22, 24 respectively, each having an inner conductive core surrounded by an outer sheath of insulating material.

- 20 The meter comprises a housing 10 formed in two parts, herein referred to as a back plate 12 and a front plate 14, moulded from an electrically insulating plastics material. The back plate 12 is a solid block having a flat rear surface 16 and a shaped front surface 18.
- 25 The back plate 12 has two holes 20 to receive fixing devices such as screws or bolts (not shown) which allow the back plate to be fastened with its rear surface 16 flat against a wall or other supporting surface (also not shown) behind the mains cables 22, 24. The latter
- 30 are, in use, placed across the front surface 18 of the back plate 12 such that each lies in and along a respective one of a pair of parallel vertical guide channels 26, 28 in the surface 18. The front surface

18 also has a pair of recesses 30 disposed closely one on each side of the upper end of the channel 28 containing the neutral cable 24.

- 5 The front plate 14, which is hollow to contain a printed circuit board 32 and an LCD counter 34 to be described, has a shaped rear surface 36 and a substantially flat front surface 38. The rear surface 36 has a pair of parallel vertical ribs 40, 42 and a  
10 pair of parallel projections 44 disposed closely one on each side of the upper part of the rib 42. The ribs 40, 42 and projections 44 on the rear surface 36 are shaped and located such that they are substantially complementary to the channels 26, 28 and recesses 30 in  
15 the front surface 18 of the back plate 12.

- In use, when the back plate 12 has been fixed to a wall or other support surface with the cables 22, 24 disposed in the channels 26, 28 as described, the front  
20 plate 14 is offered to the back plate 12 with the ribs 40, 42 in register with the channels 26, 28 respectively and the projections 44 in register with respective recesses 30, and the front plate is then pushed towards the back plate such that the ribs enter  
25 the channels and the projections enter the recesses. The front plate 14 is clamped to the back plate 12 in this position by means of four bolts 46 which pass through the front plate and engage respective screw-threaded inserts 48 embedded in the back plate, the  
30 bolts 46 being tightened until the rear surface 36 of the front plate comes to abut against the front surface 18 of the back plate.

As seen in Fig. 5, the width of each channel 26, 28 is substantially the same as the diameter of the respective cable 22 or 24, while the depth of each rib 40, 42 is less than the depth of the corresponding channel 26, 28 by a distance substantially the same as the diameter of the respective cable 22 or 24. Thus, when the two plates 12, 14 are clamped together as aforesaid, each cable 22, 24 is snugly accommodated in a respective vertical bore 50 of square cross-section in the housing 10.

Each rib 40, 42 has a respective electrical contact 52, Fig. 4, securely embedded therein, each contact having a pointed forward end 54 projecting centrally from the free end of the rib. Thus, when the front and back plates 12, 14 are clamped together as aforesaid, each forward end 54 of a contact 52 automatically pierces the insulating sheath of the corresponding cable 22 or 24 to establish electrical contact with the conductive core. In use, therefore, the contacts 52 tap the instantaneous voltage across the cables 22, 24.

In addition to the contacts 52 for tapping the voltage across the cables 22 and 24, the front plate 14 also contains one or more coils for sensing, by induction, the instantaneous current in the neutral cable 24 and providing an output signal corresponding to such current. In the illustrated, preferred embodiment of Figs. 3-5, such sensing is effected by a series of coils 56 (described in greater detail below with reference to Figs. 7-9) embedded in and behind the projections 44 so as to surround the cable 24 on three sides. However, the skilled person will appreciate



that the design of meter discussed above can employ any suitable current sensing means, while retaining the advantages of ease of manufacture and installation.

5 The voltage tapped by the contacts 52 and the output of the current sensing coils 56 are connected to an energy-calculating circuit (not shown) mounted on the printed circuit board 32. Such circuit may be of conventional design and is arranged to calculate, in  
10 known manner from the tapped voltage and the sensed current, the electrical energy in KWhrs supplied by the cables 22, 24. The circuit drives an LED counter 34 which displays the calculated result.

15 In order to prevent tampering with the meter, the head 46a, Fig. 6, of at least one of the bolts 46 projects from the front surface 38 of the front plate 14 and has a cross bore 58. Just below each such bolt there is a respective tab 60 projecting from and securely embedded  
20 in the front surface 38, each tab having a hole 62. A wire 64 passing through the bore 58 and hole 62 and sealed at 66 prevents the bolt 46 from being turned sufficiently to remove the front plate 14 from the back plate 12.

25

The arrangement of coils will now be described in more detail with reference to a current probe illustrated in Fig. 7.

30 The probe comprises a series of N (in this case N=7) identical Rogowski coils 56 equally spaced along the circumference of a circle.

The spacing between any pair of adjacent coils 56 may be used to insert a current conductor to be measured, such that the current-carrying conductor is partially surrounded by the circular array of coils. This arrangement suffers, to some extent, from the same effects as the probe of Fig. 2 (i.e. the voltage pickup of the probe is dependent on the location of the source conductor within the internal cross section of the coil, and the pickup from outside the core gap must be taken into account).

At this point it is useful to compare the performances of the probes shown in Figs. 2 and 7.

In the Fig. 2 design, the closer the current carrying conductor is to the gap or the windings the greater the variation in pickup. As expected, the larger the gap the larger the variation in pickup levels. However this variation can be kept within acceptable limits. For example variations of less than  $\pm 3\%$  may be obtained with gaps of about 1.6 cm if the source current conductor is confined to a rectangular area 8 (Fig. 2) which begins a distance D (approximately 10mm) from the centre of the gap and ends a distance C, (also approximately 10mm), from the continuous windings 5.

Using the design of Fig. 7 with the dimensions given above the variation in reading obtained may also be kept less than  $\pm 3\%$  if the current conductor is confined to the rectangular area 68 which is less than the width of the gap and stretches vertically from the dotted line located at distance D, where  $D=10\text{mm}$ , from the circumference diametrically opposite. This

performance is very similar to the probe design shown in Fig. 2.

However, using the design of Fig. 7, the error in  
5 measurement due to these effects gets smaller as the number N of individual coils increases.

As the number N of coils increases however, for a given diameter F of circle, the gap between individual coils  
10 decreases, as does the diameter of conductor that may be inserted. Preferably, one will use the maximum number of individual coils possible that still accommodates the largest conductor diameter required in the application. For example if the design requires a  
15 maximum source conductor diameter of 14mm and the coils are arranged in a circle having a diameter  $F=42.5\text{mm}$ , then the maximum number of individual coils that may be used is seven. This leaves space for individual coil widths G of 2mm and an enclosure thickness of 1mm.

20 A very important feature of the probe design is the pickup ratio or interference ratio R between the pickup from an external source 9 (see Fig. 2), at a distance x from the gap, and the pickup from the same source when  
25 it is located in the measurement area 8. This ratio R should be minimised.

For a typical well designed probe with the configuration of Fig. 2, Table 1 shows the calculated  
30 value of pickup ratio R, expressed as a percentage for increasing values of x expressed in mm. The dimensions of the continuous coil portion 15 of the probe are taken as 50mm long by 31mm wide in the calculations of

Table 1. These dimensions are typical for this type of probe.

| R<br>% | x<br>mm |
|--------|---------|
| 22     | 4       |
| 12     | 6       |
| 7      | 8       |
| 4      | 10      |
| 2.1    | 12      |
| 1.2    | 14      |
| 0.8    | 16      |
| 0.6    | 18      |
| 0.5    | 20      |
| 0.4    | 22      |
| 0.32   | 24      |
| 0.28   | 26      |
| 0.20   | 34      |

TABLE 1.

5

It can be seen from Table 1 that in order to maintain an error of less than 2% due to an interfering source of the same current magnitude as the source being measured, the distance x must be greater than about 12mm. Since the minimum value of D is 10mm in this design then the minimum spacing (x+D) between the interfering source and the source being measured must be greater than 22mm.

10

15 It is quite possible in the case of a distribution box, for example, that the interfering source current could be a factor of ten or more larger than the current being measured. For a factor of ten difference, the distance x to the source must be greater than 34mm in order to maintain a maximum error of less than 2% due to interference and thus the total separation between

20

measured and interfering sources would have to be greater than 44mm.

The pickup ratio  $R$  as defined above is shown in Table 2(a) for the probe of Fig. 7 having a diameter  $F$  of 42.5mm.

| $R$<br>% | $x$<br>mm |
|----------|-----------|
| 20       | 4         |
| 13.3     | 6         |
| 8.6      | 8         |
| 5.6      | 10        |
| 3.7      | 12        |
| 2.54     | 14        |
| 1.7      | 16        |
| 1.2      | 18        |
| 0.87     | 20        |

$F = 42.5\text{mm}$

$N = 7$

Table 2(a)

10

If Table 1 and Table 2(a) are compared it is seen that for values of  $x$  less than 6mm, the system of Fig. 7 is slightly better than that of Fig. 2. However, as  $x$  increases beyond 6mm the system of Fig. 7 can be better by as much as a factor of 2 at  $x=18\text{mm}$ .

Fig. 8 shows a simple embodiment of such a coil arrangement in greater detail. In Fig. 8 one can see a portion of the back plate 12 and front plate 14 in the vicinity of rib 42, projections 44, and neutral cable 24. It can be seen that neutral cable 24 is pierced by forward end 54 of contact 52, which is connected via a

20

voltage take-off conductor 60 to the PCB (not shown).  
The voltage between the live and neutral conductors is  
used to power the PCB measurement circuitry and the LCD  
display.

5

For simplicity, Fig. 8 shows a series of only five  
coils 56 arranged around the circumference of a circle,  
and connected in series. A gap between the two  
uppermost (as seen in Fig. 8) coils 56 admits neutral  
10 cable 24. The voltage generated in the series of coils  
is carried via a pair of conductors 58 to the PCB where  
the current within the neutral conductor is determined  
from the calibration of the coils 56.

15 The greater the number of equally spaced coils 56 and  
hence the smaller the gap between adjacent coils, the  
more sensitive the device will be, when this coil  
arrangement is used. Obviously, while only 5 coils are  
shown for simplicity in the Fig. 8 view, one will aim  
20 to maximise the number of coils consistent with the  
diameter of the conductor, by varying the design of the  
meter and thereby reducing the gap size.

Advantages of the meter described above are that it may  
25 be manufactured at low cost and is easy and quick to  
install to existing mains systems. It can be designed  
to use <40mwatts to power itself, being less than 2% of  
the power required by existing analog meters. It does  
not suffer from inertia and will register power at 50  
30 times lower levels than existing meters.

Furthermore, by employing the current probe arrangement of the invention, the interference from external current sources can be reduced significantly.

- 5 Although the foregoing has described an embodiment where the meter is designed for use with a single pair of live and neutral cables, the invention is applicable to other mains systems, for example with three phase and one neutral cable.

10

The current probe can be improved by adding a second set of coils. To understand how this improvement occurs, the pickup ratio  $R$  is now examined for a set of seven coils identical to those discussed above for Fig.

- 15 7, but arranged on a 46.5mm circle rather than 42.5mm.

Table 2(b) displays the pickup ratio  $R$  for this arrangement of seven coils as a function of  $x$ . The distance  $x$  in this case is measured from the

20 circumference of the larger circle.

| $R$<br>% | $x$<br>mm |
|----------|-----------|
| 25.2     | 4         |
| 17       | 6         |
| 11       | 8         |
| 8        | 10        |
| 5.4      | 12        |
| 3.7      | 14        |
| 2.6      | 16        |
| 1.9      | 18        |
| 1.37     | 20        |

$$F = 46.5\text{mm}$$

$$N = 7$$

Table 2(b)

If both sets of seven coils each are present with their diameters differing by 4mm then an interfering source at a distance  $x$  from the circumference of the inner circle would be a distance  $(x-2)$ mm from the outer circumference.

If the ratio  $R$  picked up by the inner set at a distance  $x$ , as shown in Table 2(a), is compared with that picked up from the same interference location by the outer set, at a distance  $x-2$ , as shown in Table 2(b), it is observed that they differ in level by a factor of 2 approximately, with the outer set picking up twice the interference level of the inner set approximately. For convenience, Tables 2(a) and (b) are set out again, alongside one another:

| R<br>% | x<br>mm |
|--------|---------|
| 20     | 4       |
| 13.3   | 6       |
| 8.6    | 8       |
| 5.6    | 10      |
| 3.7    | 12      |
| 2.54   | 14      |
| 1.7    | 16      |
| 1.2    | 18      |
| 0.87   | 20      |

(a)  $F = 42.5\text{mm}$   
 $N = 7$

| R<br>% | x<br>mm |
|--------|---------|
| 25.2   | 4       |
| 17     | 6       |
| 11     | 8       |
| 8      | 10      |
| 5.4    | 12      |
| 3.7    | 14      |
| 2.6    | 16      |
| 1.9    | 18      |
| 1.37   | 20      |

(b)  $F = 46.5\text{mm}$   
 $N = 7$

Table 2.



For example, a source at  $x=10\text{mm}$  from the inner coils will exhibit a pickup ratio  $R=5.6\%$  in the inner coil set. The same source is  $8\text{mm}$  from the outer coils, in which a pickup ratio of  $R=11\%$  is generated.

5

This factor 2 remains almost constant for different values of  $x$ . It is therefore possible, irrespective of the distance  $x$ , to cancel out a large proportion of the interference by subtracting approximately half the voltage picked up by the outer set from that picked up by the inner set. The factor of 0.5 is approximately the correct factor to use for these two particular coil set diameters each comprising seven identical coils.

10  
15 For greater differences between the inner and outer coil set diameters there is an increase in the factor by which the interference pickup from the outer set is greater than that of the inner set. To compensate, therefore, one must subtract a smaller amount of the  
20 outer set pickup from that of the inner set in order to minimise interference. Best cancellation of interference at all distances  $x$  is obtained by minimising the difference between the diameters of both sets of coils that are used. Preferably the individual  
25 coil diameters (dimension "T" in Fig. 7) are reduced to assist in this regard.

The configuration of this minimum interference probe is shown in Fig. 9 together with a front end amplifier 70.  
30 The factor of pickup voltage from the outer set that is subtracted from the voltage pickup of the inner set is directly proportional to the ratio of resistor values  $R1/R2$ .

Table 3 shows the interference ratio R as a function of x for the coil arrangement of Fig. 9. In this table x is measured as the distance outwards from a point

- 5 midway between the inner and outer circumferences. The results shown are for an inner diameter  $F1=42.5\text{mm}$  and an outer diameter  $F2 = 47.5\text{mm}$ .  $R1$  is chosen to be 0.52  $R2$  in this design so that the effective input signal is the voltage pickup from the inner set minus 0.52 times  
10 the pickup from the outer set.

- If one compares the values of pickup ratio R of Table 3 to those of Table 1 (i.e. comparing the configuration of Fig. 9 with that of Fig. 2) it is seen that the  
15 interference of this new probe is far less than that of the old probe at any distance x. In fact the rejection is a minimum factor of 3.7 lower at  $x = 4\text{mm}$  and increases to a factor of 33 lower at  $x = 20\text{mm}$ .

- 20 The configuration of Fig. 9 thus shows significant advantages over the configuration of Fig. 2 allowing the use of smaller probes with less interference.

| R<br>% | X<br>mm |
|--------|---------|
| 6      | 4       |
| 2.4    | 6       |
| 0.95   | 8       |
| 0.41   | 10      |
| 0.18   | 12      |
| 0.08   | 14      |
| 0.04   | 16      |
| 0.024  | 18      |
| 0.15   | 20      |

In preferred probes according to the invention,  
therefore, the double coil arrangement of Fig. 9 may be  
used, subject to design variations in dimensions and  
5 numbers of coils.

A particularly preferred energy meter according to the  
invention incorporates, as its sensing means, the probe  
design of Fig. 9.

10

The invention is not limited to the embodiments  
described herein which may be modified or varied  
without departing from the scope of the invention.

11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000 1001 1002 1003 1004 1005 1006 1007 1008 1009 1010 1011 1012 1013 1014 1015 1016 1017 1018 1019 1020 1021 1022 1023 1024 1025 1026 1027 1028 1029 1030 1031 1032 1033 1034 1035 1036 1037 1038 1039 1040 1041 1042 1043 1044 1045 1046 1047 1048 1049 1050 1051 1052 1053 1054 1055 1056 1057 1058 1059 1060 1061 1062 1063 1064 1065 1066 1067 1068 1069 1070 1071 1072 1073 1074 1075 1076 1077 1078 1079 1080 1081 1082 1083 1084 1085 1086 1087 1088 1089 1090 1091 1092 1093 1094 1095 1096 1097 1098 1099 1100 1101 1102 1103 1104 1105 1106 1107 1108 1109 1110 1111 1112 1113 1114 1115 1116 1117 1118 1119 1120 1121 1122 1123 1124 1125 1126 1127 1128 1129 1130 1131 1132 1133 1134 1135 1136 1137 1138 1139 1140 1141 1142 1143 1144 1145 1146 1147 1148 1149 1150 1151 1152 1153 1154 1155 1156 1157 1158 1159 1160 1161 1162 1163 1164 1165 1166 1167 1168 1169 1170 1171 1172 1173 1174 1175 1176 1177 1178 1179 1180 1181 1182 1183 1184 1185 1186 1187 1188 1189 1190 1191 1192 1193 1194 1195 1196 1197 1198 1199 1200 1201 1202 1203 1204 1205 1206 1207 1208 1209 1210 1211 1212 1213 1214 1215 1216 1217 1218 1219 1220 1221 1222 1223 1224 1225 1226 1227 1228 1229 1230 1231 1232 1233 1234 1235 1236 1237 1238 1239 1240 1241 1242 1243 1244 1245 1246 1247 1248 1249 1250 1251 1252 1253 1254 1255 1256 1257 1258 1259 1260 1261 1262 1263 1264 1265 1266 1267 1268 1269 1270 1271 1272 1273 1274 1275 1276 1277 1278 1279 1280 1281 1282 1283 1284 1285 1286 1287 1288 1289 1290 1291 1292 1293 1294 1295 1296 1297 1298 1299 1300 1301 1302 1303 1304 1305 1306 1307 1308 1309 1310 1311 1312 1313 1314 1315 1316 1317 1318 1319 1320 1321 1322 1323 1324 1325 1326 1327 1328 1329 1330 1331 1332 1333 1334 1335 1336 1337 1338 1339 1340 1341 1342 1343 1344 1345 1346 1347 1348 1349 1350 1351 1352 1353 1354 1355 1356 1357 1358 1359 1360 1361 1362 1363 1364 1365 1366 1367 1368 1369 1370 1371 1372 1373 1374 1375 1376 1377 1378 1379 1380 1381 1382 1383 1384 1385 1386 1387 1388 1389 1390 1391 1392 1393 1394 1395 1396 1397 1398 1399 1400 1401 1402 1403 1404 1405 1406 1407 1408 1409 1410 1411 1412 1413 1414 1415 1416 1417 1418 1419 1420 1421 1422 1423 1424 1425 1426 1427 1428 1429 1430 1431 1432 1433 1434 1435 1436 1437 1438 1439 1440 1441 1442 1443 1444 1445 1446 1447 1448 1449 1450 1451 1452 1453 1454 1455 1456 1457 1458 1459 1460 1461 1462 1463 1464 1465 1466 1467 1468 1469 1470 1471 1472 1473 1474 1475 1476 1477 1478 1479 1480 1481 1482 1483 1484 1485 1486 1487 1488 1489 1490 1491 1492 1493 1494 1495 1496 1497 1498 1499 1500 1501 1502 1503 1504 1505 1506 1507 1508 1509 1510 1511 1512 1513 1514 1515 1516 1517 1518 1519 1520 1521 1522 1523 1524 1525 1526 1527 1528 1529 1530 1531 1532 1533 1534 1535 1536 1537 1538 1539 1540 1541 1542 1543 1544 1545 1546 1547 1548 1549 1550 1551 1552 1553 1554 1555 1556 1557 1558 1559 1560 1561 1562 1563 1564 1565 1566 1567 1568 1569 1570 1571 1572 1573 1574 1575 1576 1577 1578 1579 1580 1581 1582 1583 1584 1585 1586 1587 1588 1589 1590 1591 1592 1593 1594 1595 1596 1597 1598 1599 1600 1601 1602 1603 1604 1605 1606 1607 1608 1609 1610 1611 1612 1613 1614 1615 1616 1617 1618 1619 1620 1621 1622 1623 1624 1625 1626 1627 1628 1629 1630 1631 1632 1633 1634 1635 1636 1637 1638 1639 1640 1641 1642 1643 1644 1645 1646 1647 1648 1649 1650 1651 1652 1653 1654 1655 1656 1657 1658 1659 1660 1661 1662 1663 1664 1665 1666 1667 1668 1669 1670 1671 1672 1673 1674 1675 1676 1677 1678 1679 1680 1681 1682 1683 1684 1685 1686 1687 1688 1689 1690 1691 1692 1693 1694 1695 1696 1697 1698 1699 1700 1701 1702 1703 1704 1705 1706 1707 1708 1709 1710 1711 1712 1713 1714 1715 1716 1717 1718 1719 1720 1721 1722 1723 1724 1725 1726 1727 1728 1729 1730 1731 1732 1733 1734 1735 1736 1737 1738 1739 1740 1741 1742 1743 1744 1745 1746 1747 1748 1749 1750 1751 1752 1753 1754 1755 1756 1757 1758 1759 1760 1761 1762 1763 1764 1765 1766 1767 1768 1769 1770 1771 1772 1773 1774 1775 1776 1777 1778 1779 1780 1781 1782 1783 1784 1785 1786 1787 1788 1789 1790 1791 1792 1793 1794 1795 1796 1797 1798 1799 1800 1801 1802 1803 1804 1805 1806 1807 1808 1809 1810 1811 1812 1813 1814 1815 1816 1817 1818 1819 1820 1821 1822 1823 1824 1825 1826 1827 1828 1829 1830 1831 1832 1833 1834 1835 1836 1837 1838 1839 1840 1841 1842 1843 1844 1845 1846 1847 1848 1849 1850 1851 1852 1853 1854 1855 1856 1857 1858 1859 1860 1861 1862 1863 1864 1865 1866 1867 1868 1869 1870 1871 1872 1873 1874 1875 1876 1877 1878 1879 1880 1881 1882 1883 1884 1885 1886 1887 1888 1889 1890 1891 1892 1893 1894 1895 1896 1897 1898 1899 1900 1901 1902 1903 1904 1905 1906 1907 1908 1909 1910 1911 1912 1913 1914 1915 1916 1917 1918 1919 1920 1921 1922 1923 1924 1925 1926 1927 1928 1929 1930 1931 1932 1933 1934 1935 1936 1937 1938 1939 1940 1941 1942 1943 1944 1945 1946 1947 1948 1949 1950 1951 1952 1953 1954 1955 1956 1957 1958 1959 1960 1961 1962 1963 1964 1965 1966 1967 1968 1969 1970 1971 1972 1973 1974 1975 1976 1977 1978 1979 1980 1981 1982 1983 1984 1985 1986 1987 1988 1989 1990 1991 1992 1993 1994 1995 1996 1997 1998 1999 2000 2001 2002 2003 2004 2005 2006 2007 2008 2009 2010 2011 2012 2013 2014 2015 2016 2017 2018 2019 2020 2021 2022 2023 2024 2025 2026 2027 2028 2029 2030 2031 2032 2033 2034 2035 2036 2037 2038 2039 2040 2041 2042 2043 2044 2045 2046 2047 2048 2049 2050 2051 2052 2053 2054 2055 2056 2057 2058 2059 2060 2061 2062 2063 2064 2065 2066 2067 2068 2069 2070 2071 2072 2073 2074 2075 2076 2077 2078 2079 2080 2081 2082 2083 2084 2085 2086 2087 2088 2089 2090 2091 2092 2093 2094 2095 2096 2097 2098 2099 2100 2101 2102 2103 2104 2105 2106 2107 2108 2109 2110 2111 2112 2113 2114 2115 2116 2117 2118 2119 2120 2121 2122 2123 2124 2125 2126 2127 2128 2129 2130 2131 2132 2133 2134 2135 2136 2137 2138 2139 2140 2141 2142 2143 2144 2145 2146 2147 2148 2149 2150 2151 2152 2153 2154 2155 2156 2157 2158 2159 2160 2161 2162 2163 2164 2165 2166 2167 2168 2169 2170 2171 2172 2173 2174 2175 2176 2177 2178 2179 2180 2181 2182 2183 2184 2185 2186 2187 2188 2189 2190 2191 2192 2193 2194 2195 2196 2197 2198 2199 2200 2201 2202 2203 2204 2205 2206 2207 2208 2209 2210 2211 2212 2213 2214 2215 2216 2217 2218 2219 2220 2221 2222 2223 2224 2225 2226 2227 2228 2229 2230 2231 2232 2233 2234 2235 2236 2237 2238 2239 2240 2241 2242 2243 2244 2245 2246 2247 2248 2249 2250 2251 2252 2253 2254 2255 2256 2257 2258 2259 2260 2261 2262 2263 2264 2265 2266 2267 2268 2269 2270 2271 2272 2273 2274 2275 2276 2277 2278 2279 2280 2281 2282 2283 2284 2285 2286 2287 2288 2289 2290 2291 2292 2293 2294 2295 2296 2297 2298 2299 2300 2301 2302 2303 2304 2305 2306 2307 2308 2309 2310 2311 2312 2313 2314 2315 2316 2317 2318 2319 2320 2321 2322 2323 2324 2325 2326 2327 2328 2329 2330 2331 2332 2333 2334 2335 2336 2337 2338 2339 2340 2341 2342 2343 2344 2345 2346 2347 2348 2349 2350 2351 2352 2353 2354 2355 2356 2357 2358 2359 2360 2361 2362 2363 2364 2365 2366 2367 2368 2369 2370 2371 2372 2373 2374 2375 2376 2377 2378 2379 2380 2381 2382 2383 2384 2385 2386 2387 2388 2389 2390 2391 2392 2393 2394 2395 2396 2397 2398 2399 2400 2401 2402 2403 2404 2405 2406 2407 2408 2409 2410 2411 2412 2413 2414 2415 2416 2417 2418 2419 2420 2421 2422 2423 2424 2425 2426 2427 2428 2429 2430 2431 2432 2433 2434 2435 2436 2437 2438 2439 2440 2441 2442 2443 2444 2445 2446 2447 2448 2449 2450 2451 2452 2453 2454 2455 2456 2457 2458 2459 2460 2461 2462 2463 2464 2465 2466 2467 2468 2469 2470 2471 2472 2473 2474 2475 2476 2477 2478 2479 2480 2481 2482 2483 2484 2485 2486 2487 2488 2489 2490 2491 2492 2493 2494 2495 2496 2497 2498 2499 2500 2501 2502 2503 2504 2505 2506 2507 2508 2509 2510 2511 2512 2513 2514 2515 2516 2517 2518 2519 2520 2521 2522 2523 2524 2525 2526 2527 2528 2529 2530 2531 2532 2533 2534 2535 2536 2537 2538 2539 2540 2541 2542 2543 2544 2545 2546 2547 2548 2549 2550 2551 2552 2553 2554 2555 2556 2557 2558 2559 2560 2561 2562 2563 2564 2565 2566 2567 2568 2569 2570 2571 2572 2573 2574 2575 2576 2577 2578 2579 2580 2581 2582 2583 2584 2585 2586 2587 2588 2589 2590 2591 2592 2593 2594 2595 2596 2597 2598 2599 2600 2601 2602 2603 2604 2605 2606 2607 2608 2609 2610 2611 2612 2613 2614 2615 2616 2617 2618 2619 2620 2621 2622 2623 2624 2625 2626 2627 2628 2629 2630